

## **CP.BN**





# INTERNAL CONTROL PANELS 24 Vdc



#### **APPLICATION**

2 actuators for BEN series swing gates

### **CONTROL PANEL POWER SUPPLY**

230 Vac

#### **MOTORS POWER SUPPLY**


24 Vdc 50W + 50W

#### **MAIN FUNCTIONS:**

- · Built-in LCD display
- Built-in 433.92 MHz 64 codes and 2 codes radio receiver (programmable code and rolling code)
- · Removable terminal blocks
- Pedestrian input
- Gate open indicator light output, service light and second radio channel
- · Operating parameters autoset
- Electronic adjustment of individual couple for each motor
- Amperometric sensor obstacle detection security to prevent crushing
- Independent decelerations during open and close for each motor
- Optional parameter configuration and remote control management using the Advantouch system
- Number of manoeuvres







# **ACCESSORIES**



#### DU.V96 9765035

12 Vac/dc vertical electric lock, supplied with counterplate. Permits internal/ external release.



DU.V90

9765030 12 Vac/dc horizontal electric lock, supplied with counterplate. Permits internal/ external release.



**DU.9990** 9623010

Covering plate for



**L.BY** 9760024

Control board for electric lock 12/24 Vdc.



SC.RD

9760027

Board no. 4 relays for control unit inputs support/decoupling. For use in the event of very long connections (i.e. buttons in house).



## BN.CB

9760072

Accessory for CP.BN composed of battery charger card CBY.24V, 1,2Ah batteries and support for batteries.



